



Coax: Beyma 12XA30Nd 35Hz-20KHz/350+90W/8ohm 80° conical - baspoort 2x 6,86Ø*9,7cm 62,5Hz - 21KHz -6dB
 passief filter 1800Hz 12/18dB/okt + Lpad of Beyma FD2XA crossover 96,0dB 1W/1M 450W AES / 8ohm

Coax: B&C 12FCX76 55Hz-20KHz/350+80W/8ohm 80° conical - baspoort 2x 6,86Ø*15,6cm 55,0Hz - 21KHz -6dB
 passief filter 1200Hz 12/18dB/okt + Lpad of B&C XO-3 crossover 96,0dB 1W/1M 450W AES / 8ohm

Model	Enclosure Design	Frequency Response	Efficiency	Power / imp.
12coax	Fullrange vented	67,5Hz - 21KHz -6dB	98,5dB 1W/1M	350W AES / 8ohm
Components	Kast: Berken multiplex 15mm			Netto inhoud: 35,5Ltr
	Coax: RCF CX12G251 55Hz-20KHz/300+50W/8ohm 60° conical			
	LKDX113 - Link Dynamics Custom 2-way Crossover RCF CX12G251			

Ontwerp: van den Hoogen's Servicebedrijf / Boi van den Hoogen / www.soundshopschylge.nl / 17-07-2018

passief filter Convair CNVX911 67,5Hz - 21KHz -6dB 97,5dB 1W/1M 500W AES / 8ohm

Coax: P-audio SN12-500CX 55Hz-20KHz/500W/8ohm 60° conical - baspoort 2x 6,86Ø*6,7cm 65,0Hz - 21KHz -6dB